

SINGLE PHASE
230 V / 50 Hz
GASOLINE

MAX OUTPUT
4 kW


LONG RUN
TANK

SOUND PROOF
67 dB(A) at 7 m

WHEELS & HANDLE
INCLUDED



3 YEARS
WARRANTY



NEW

Equipped with the inverter technology, this generator delivers a perfect quality of current, voltage and a very stable frequency which make it possible to use even with the most sensitive devices (computers, electronic equipments...). Equipped with the automatic idling system, the engine speed can be automatically adjusted to the required power which reduces consumption and noise. Transportable and soundproofed, this unit is ideal for all types of users and applications, professional, on site and leisure activities. With its coupling function, you can connect in parallel two ACCESS 4000 i and double the available power. It gives you a more powerful generator avoiding the question of additional weight and dimension increase.

ACCESS 4000 i

Type		1 phase
Voltage regulator		INVERTER
Maximum AC output	kW	4
Continuous operating power (COP)	kW	3.6 (7.2 kW paired)
Maximum Amps	A	17.3
AC voltage	V	230
Frequency	Hz	50
Noise level EEC (LwA)	dB(A)	92
Noise level @ 7 m	dB(A)	67
Engine		WORMS G225-i
Maximum output	HP	6.4
Fuel type		Unleaded gasoline 95
Fuel tank capacity	L	10
Run Time (@ ¾ of the continuous output)	h	5
Dimensions L x W x H	mm	605 x 432 x 493
Packaging dimensions L x W x H	mm	625 x 490 x 565
Net weight	kg	41
Gross weight	kg	44.5
Reference		200100007

STANDARD EQUIPMENT

- ✓ 4-stroke OHV gasoline engine
- ✓ Recoil starter
- ✓ Oil sensor with warning light
- ✓ Automatic idling system
- ✓ 2 Single phase sockets 10/16 A Schuko 230 V
1 Single phase socket 10/16 A Schuko 230 V with
Circuit breaker kit option
- ✓ Sockets protected by thermal circuit breaker
- ✓ USB charger
- ✓ Parallel operation socket
- ✓ Electronic overload protection with warning light
- ✓ Sound proof canopy
- ✓ Integrated wheels and carrying handle

OPTIONAL EQUIPMENT

- ✓ Cables for parallel operation
- ✓ Circuit breaker kit (factory option): 30 mA circuit breaker
in Box + Copper Ground Rod